

Definition

A constructed barrier to animals.

Purpose

Facilitate the application of conservation practices by providing a means to control movement of animals.

Conditions Where Practice Applies

This practice may be applied on any area where management of animal movement is needed. Fences are not needed where natural barriers will serve the purpose.

General Criteria and Specifications

A. Permanent Fence

Permanent electric fences shall be High Tensile Wire (HTW) constructed with the intent of being in place for the life of the practice. Permanent fences will have a minimum of three strands of wire. Electric fences provide psychological deterrent rather than a physical barrier to livestock and wildlife. To be effective, a shock of at least 1,000 volts must be delivered to cattle, 2,000 volts to sheep, and 2,500 to 3,000 volts to deer, dogs, and coyotes.



Photo: Virginia NRCS

B. Wire

Wire shall be a single strand of 12 – ½ gauge or larger with a minimum tensile strength of 110,000 pounds per square inch. The wire shall be galvanized (Type III), aluminum, or copper clad. Wire will be attached to the posts by a method that allows wire to slip. Wires will be attached to stays in a manner that prevents stay slippage along the fence. Initially, tension wires to 200 lbs and adjust tension of each wire to maintain the wires at the appropriate height, as necessary. Wire heights and spacing are shown by intended use in Table 1.

Barbed wire will not be used on electric fences because it is a safety hazard.

Table 1: Number of Wire and Wire Heights

Fence Description	# of Wires		Wire Ht (in.)
	Permanent	Temporary	
Internal/Cross			
Cow/Calf & Stocker	3	1	30 to 34
Swine	3	1	12
Cow/Calf & Stocker	3	2	22; 32
Sheep & Cattle	3	N/A	10; 20; 32
	4	N/A	10; 20; 32; 46
Perimeter Fence			
Cattle, Horses, Sheep (Non-Predator)	5	N/A	10; 20; 30; 40; 50
Sheep, Goats (Predator)	8	N/A	4; 8; 12; 18; 24; 30; 40; 52

C. Temporary Fence

Temporary electric fence is constructed with the intent of being left in place for only a short period of time in areas where the confinement of livestock is not absolutely critical, for example, temporary paddock divisions or strip grazing. The fence is not intended as a substitute or

equivalent of permanent fence. The temporary fence requires materials, design, and construction that will accomplish the intended purpose and last for the planned time period with limited maintenance.

High Tensile Wire is suitable for both permanent and temporary fencing. However, many companies market portable fence systems that use materials such as polyethylene wire and tape with steel and aluminum wire woven within, aluminum wire, plastic and fiberglass posts, reels to roll up wire, and battery operated energizers that are high voltage and low impedance. A minimum of six strands of steel or aluminum should be woven into the polywire or polytape. Temporary fences may be attached to permanent fences to subdivide pasture. Follow manufacturer's directions for construction, use, and operation of temporary electric fences.

All Electric Fences (Temporary and Permanent)

D. Energizers

Electronic energizers of power fence controllers shall be installed according to manufacturer's recommendations. The energizers shall be high power, low impedance with 5,000 volt peak output and a pulse that is less than 300 mAmps in intensity, finished within 0.0003 of a second and at a rate of 35 – 65 pulses per minute. Energizers shall be provided with high impact weather resistant cases. Circuitry shall be solid state. Service modules shall be snap-in for fast field repair. A safety fuse to prevent over pulsing shall be provided. The system shall be 110 volt, 220 volt, or 12-volt battery powered. The battery-powered system shall be capable of working for at least 3 weeks without replacing the battery. If the length of the fence requires more than 4 joules (watts x seconds = joules), a solar charger will be needed for 12 volt systems. The energizer shall be capable of producing one joule for each mile of planned fence when average energy loss is expected.

E. Grounding

All electric fences must be properly grounded. The energizer ground wire should be connected to a galvanized pipe or rod ½ inches or larger in diameter. Bury 3 feet of ground rod for each joule of energy output. Ground rods should be buried where soil remains moist for best results. Ground rods should be driven into the ground at least 10 feet apart when multiple rods are necessary to provide the required length of ground rod. Normally, individual ground rods will be driven no more than 6 to 8 feet into the ground. Connect a continuous ground wire from the energizer to each ground rod with

aluminum or galvanized steel clamp. If energizer terminals are not stainless steel or copper, do not use copper ground rods due to corrosion at the connection and subsequent loss of electrical continuity. Copper rods with copper wire may be used if energizer terminals are stainless steel or copper. Use copper clamps with copper wire and copper rods.

The ground wire(s) of the fence may be connected to the same ground as the energizer or to a separate ground with the same size and depth requirements. More ground rods may be needed for the system to function properly. Do not use the grounding system for other existing applications, such as power poles, breaker boxes and milk barns. At least 25 feet should separate the fence grounding system from any other grounding system.

Lightening can cause damage to the energizer. Most energizers are poorly protected from damage caused by lightning. External lightning arrestors and an induction loop (lightning choke) will be installed for added protection. Lightning arrestor grounding rods will be placed at least 65 feet from those of the energizer.

Install an additional set of ground rods and attach to a lightning arrestor. The lightning arrestor ground must be better than the energizer ground for it to function properly, because lightning will seek the path of least resistance to ground. Use at least 1 more ground rod on the arrestor than was used on the energizer. Attach the lightning arrestor to the wires of the fence. Install a lightning choke in the fence line immediately between the lightning arrestor and the energizer.

For 120 or 240-volt energizers a voltage spike protector will be used to protect energizer. Also, a ground rod should be installed at electric utility's transformer pole (primary ground) and another ground rod installed at the electrical circuit breaker box (secondary ground). Additionally, a surge protector should be installed between the energizer and power supply.

F. Insulation and Insulators

Insulation used for positive charged wire(s) must be high-density polyethylene with ultra-violet stabilizer or high-density polypropylene with ultra-violet stabilizer.

Insulators for conductive material posts, end, corner and angle braces shall be high-density polyethylene with ultra-violet stabilizer, high-density polypropylene with ultra-violet stabilizer, or porcelain. All insulators shall be capable of withstanding 10,000 volts or more of current

leakage. Red insulators attract hummingbirds and should not be used.

G. Corners, Braces, and End Assemblies

Braces and end assemblies are required at all corners, gates, and angles in the fence line.

For multi-wire permanent electric HTW fences, corner, gate, end assemblies use one of the following:

- Steel “T” post that are a minimum of 1.33 pounds per foot of length, with appropriate knee, deadman, angle or H-brace.
- Wood posts with a minimum top diameter of 5.0 inches set two feet in the ground with appropriate knee, deadman, angle, or H-brace.
- Wood, steel pipe, with a minimum top diameter of 5 inches (wood) or 2 – ½ inches (steel), set to a depth equal to, or greater than, the height of the post above the ground without bracing.
- Steel pipe with a minimum diameter of 2 – 1/2 inches, set 2 feet in the ground with appropriate knee, angle, or H-brace, deadman or anchor plate.
- Steel pipe with a minimum diameter of 2 – 1/2 inches and set in concrete to a depth of 2 feet.

For 3 or more wire power fences; corner, gate, end and brace assemblies will be either a floating angle brace or H-brace assembly. Brace assemblies will be 4 inch nominal wood, 4”x4” timber, or 2 – ½ inch nominal steel pipe (capped), with appropriate appurtenances for corner and end bracing. Posts must be set a minimum of 2 feet in the ground.

All wood posts shall be at least 2 inches higher than the top wire of the fence. Posts of any other material shall be at least 1 inch higher than the top wire of the fence.

H. Line Posts and Stays

Line post and stays will be either:

- Fiberglass, rigid plastic and PVC solid round sucker rod of at least 5/8 inch diameter, or fiberglass “T” post and stays of at least 1 inch in cross-section (temporary fence only). Attach wire to the post with loose wire clips or run the wire through holes in the post. Attach the wire to stays with tight clips.

- Wood posts at least 3 inches in diameter of black locust, red cedar, osage orange, redwood, pressure treated pine or any other wood of equal life and strength may be used. At least one half of the diameter of the red cedar and redwood post shall be heartwood. Pressure treated posts shall be treated with pentachlorophenol, or chromate copper arsenate (CCA) by a method which ensures the complete penetration of the sapwood. Insulators shall attach wire.

- Steel “U” or “T” posts that are a minimum of 1.25 pounds per foot length. Wire shall be attached with insulators. Every 4th post shall be wood.

Posts for one or two wire fences shall be long enough to be set at least 18 inches in the ground, except that in soils which are sandy loam or coarser in texture, the posts shall be set at least 24 inches into the ground. Posts for 3 or more wire fences shall be set at least 24 inches into the ground. Posts in dips shall be constructed so that they do not pull out of the soil. Posts 2 inch or smaller shall be anchored. Wood posts shall be set to a depth sufficient to resist pull out.

Wood posts shall be at least 2 inches higher than the top wire on the fence. All other posts shall be at least 1 inch higher than the top wire of the fence.

Spacing of the line posts and stays depends on the terrain and the number of wires. Maximum spacing is as follows:

- One or two wire fences may have line posts spaced up to 100 feet apart with no stays. Line posts may be spaced 150 feet apart with stays every 50 feet between the posts.
- For three and four wire fences, the line posts may be spaced every 50 feet with no stays or every 150 feet with stays at spacing of not more than every 50 feet.
- Fences with more than 4 wires shall have posts and stays spaced every 30 feet, with posts not further apart than every 90 feet.
- In undulating terrain, space posts and stays as needed to maintain the fence height.

I. Gates

Electrified gates may be constructed of a single straight wire, galvanized cable, or polytape with a insulated spring loaded handle or an expandable, coiled, high

tensile, 12 – ½ gauge wire attached to an insulated handle. The number of wires shall be determined by the objective of the fence. The gate shall be constructed so that it is non-electrified when the gate is open.

Overhead or underground transmission lines will be used to carry electricity past the gate to the remainder of the fence.

Use insulated galvanized wire for crossing gates and areas where electrical shocks to livestock and humans are undesirable. All underground wires must be insulated for a minimum of 15,000 volts. Insulated underground wire should be specifically designed for high voltage electric fence. The insulation shall be high-density polyethylene with ultra-violet stabilizer or high-density polypropylene with ultra-violet stabilizer. Placing buried wire inside plastic pipe helps to decrease the likelihood of short circuiting. Overhead transmission lines shall be at a height where the lines do not impede movement of livestock or equipment.

An electrified flood gate may be used in lieu of a non-electrified gate. The electrified floodgate should be constructed by stretching an electrified wire across the drainage above the high water level. Attach droppers of 12 – ½ gauge high tensile fence wire, galvanized cable or galvanized chains to the electrified wire at a spacing of 6 inches for sheep and 12 inches for cattle. The droppers shall be extended to approximately 6 inches above normal water level. Connect gate to electric fence with a double insulated cable through a cutoff switch and flood control gate controller. If flooding is expected to last for an extended period of time, switch the floodgate off.

Panel gates, if used, shall be equivalent in quality to the fencing criteria contained in the Fence: Barbed and Woven Wire job sheet and shall be fitted with at least two hinges and a latch or galvanized chain for fastening.

Other Considerations

A. Approved Alternative Fence Systems

Approve alternative fencing systems include several variations of special or non-conventional fencing systems that are acceptable when installed according to manufacturer's recommendations and pre-approved by an NRCS Area Resource Conservationist (ARC) or Area Engineer (AE). Alternative fence systems are often applicable for horses and animals having special needs.

B. Alternative Fencing and Bracing Systems

Alternative fencing and bracing systems must meet NRCS expected life span of the practice, be pre-approved by an NRCS ARC or AE, and must be installed according to manufacturer's recommendations as approved by the ARC or AE.

Operation and Maintenance

Regular inspection of fences should be part of an on-going management program. Inspection of fences at regular intervals and after storm events is needed to facilitate the function of the intended use of the fence. Maintenance and repairs will be performed as needed to facilitate the operation of the fence.

Specifications

Site-specific requirements are listed on the specifications sheet. Additional provisions are entered on the job sketch. Specifications are prepared in accordance with the NRCS Field Office Technical Guide. See Conservation Practice Standard – Fence (382).

Client:		Farm #:			
Field(s):		Tract #:			
Planned By:		Location:			
Date:		Length of Fence (ft):			
Landowner Objectives:					
Purpose: (check all that apply)					
<input type="checkbox"/> Reduce erosion and improve water quality by controlling livestock access to streams, springs, wetlands, and ponds.		<input type="checkbox"/> Protect sensitive environmental areas and flora from vehicular, pedestrian, or animal traffic use.			
<input type="checkbox"/> Protect newly planted areas from disturbances until established.		<input type="checkbox"/> Protect the safety of people, livestock, and wildlife by limiting or denying access to hazardous areas.			
<input type="checkbox"/> Facilitate handling, movement, and feeding of livestock in the pasture environment.		<input type="checkbox"/> Improve distribution and timing of livestock grazing			
<input type="checkbox"/> Other (specify)					
Electric High Tensile Fence					
Type	Type of Wire	# of Strands & Strands Electrified	Wire Spacing (in)	Fence Height (ft)	Tensioned Properly (Y or N)
Permanent					
Temporary/Portable					
Alternative System (ARC or AE - approval required)					
System Voltage					
<input type="checkbox"/> 110 volts		<input type="checkbox"/> 220 volts		<input type="checkbox"/> Battery and/or Solar	

Fence – Electric Fence (382)

Line Posts (check all that apply)	
<p>Type:</p> <input type="checkbox"/> Fiberglass, rigid plastic and PVC solid round sucker rod of at least 5/8 inch diameter; or fiberglass "T" post and stays of at least 1 inch in cross section or <input type="checkbox"/> Black Locust, Red Cedar, Osage Orange, Redwood or pressure treated or other preservative wood. or <input type="checkbox"/> Steel "U" or "T" posts that are a minimum of 1.25 lbs per ft of length.	<p>Size:</p> <input type="checkbox"/> Line posts are wood 6 – ½ feet or longer 3" minimum diameter. or <input type="checkbox"/> 6 - Standard steel line post with anchor plate. or <input type="checkbox"/> Temporary fence – 4.5 inch diameter posts set 18" into ground
<p>Maximum Spacing:</p> <input type="checkbox"/> For 1 or 2 wire fences may have line posts and stays up to 100 ft w/o stays or 150 ft w/stays every 50 ft between posts or <input type="checkbox"/> For 3 or 4 wire fences, the line posts may be spaced every 50 ft w/o stays or every 150 ft with stays not more than 50 ft apart. <input type="checkbox"/> or For 4 or more wires shall have posts and stays spaced every 30 ft, with posts not further apart than every 90 ft.	
Braces (check all that apply)	
<p>Braces, Corners, Ends, & Gates For 1 and 2 Wire Fences:</p> <input type="checkbox"/> Steel "T" post that are a minimum of 1.33 lbs/ft of length, with appropriate knee, deadman, angle, or H-brace. or <input type="checkbox"/> Wood posts with a minimum top diameter of 5.0 inches set 2 feet in the ground with appropriate knee, deadman, angle, or H-brace. or <input type="checkbox"/> Wood, steel pipe, with a minimum top diameter of 5 inches (wood) or 2 – ½ inches (steel), set to a depth equal to or greater than the height of the post above the ground without bracing. or <input type="checkbox"/> Steel pipe with a minimum diameter of 2 - ½ inches and set in concrete to a depth of 2 feet. <p>For 3 or more Wire Fences:</p> <input type="checkbox"/> Wood posts of 5.0 inch nominal diameter set a minimum of 2 feet into ground. or <input type="checkbox"/> Steel posts of 2 – 1/2 inches in diameter and capped set a minimum of 2 feet into ground. or <input type="checkbox"/> Steel "T" posts (1.33 lbs/ft of length) set a minimum of 2 feet into ground with appropriate appurtenances for corner and end bracing. <p>Bracing: (3' above ground and 8" below top of post)</p> <input type="checkbox"/> Wooden bracing at least 4 inches in diameter or <input type="checkbox"/> Wooden timber with a cross-sectional dimension of 4"x4". or <input type="checkbox"/> Steel posts of 2 – ½ inches in diameter.	<p>Brace Wire</p> <input type="checkbox"/> High tensile, galvanized steel, 9 gauge or <input type="checkbox"/> 12 – ½ gauge high tensile, galvanized, double wrapped.
Gate(s): (check all that apply)	
<input type="checkbox"/> Single, straight wire	<input type="checkbox"/> Galvanized cable
<input type="checkbox"/> Polytape with a insulated spring-loaded handle	<input type="checkbox"/> Expandable, coiled, high tensile, 12 – ½ gauge wire with insulated handle
<input type="checkbox"/> Non-electrified gate	

Layout Sketch and Drawing
(Provide sketch, drawings, maps, and/or aerial photos)

Scale 1" = _____ ft. (NA indicates sketch not to scale: grid size = 1/2" by 1/2")